

- Our finest: sensitive, sophisticated, easy to operate
- Locates 200 animals; punch in each frequency number on digital display
- Responsive to both strong and weak signals for precise direction location
- 1000 KHz frequency range avoids interference with other signals
- Attenuator prevents swamping, insures accurate close-in tracking
- Noise-blanking circuit reduces unwanted signals
- Signal meter needle deflects to show signal strength
- Signal meter is backlit to enhance night tracking
- Flashing LED (light emitting diode) matches signal beep
- Weight, less than 2 pounds. Dimensions, 7 x 4" x 4 1/2"
- Rechargeable nicad batteries give 6-8 tracking hours on full charge
- DC cord allows for external operation from vehicle's 12 v cigarette lighter
- Recharge unit, DC power cord and leather carrying case are included
- Optional lid-mounted throwaway batteries for use away from current
- Five year warranty on parts and labor



## Engineering Specifications:

Noise Figure:	2.5 dB or better
Input Impedance:	50 ohms +/- 10%
Frequency Range:	Standard bands are 150-151 MHz, 150.8-151.8 MHz, 151-152 MHz, 160-161 MHz, 164-165 MHz, 216-217 MHz, 217-218 MHz, 218-219 MHz, 220-221MHz, Other bands available on request
Frequency Stability:	+/- 1 KHz maximum (-20 degrees to +70 degrees C)
	Image and Spurious Rejection: 60 db or better
	Minimum Discernible Signal: -150 dBm (.007 microvolts) or better

### BlueSky Telemetry

The Corner, Crieff Road, Aberfeldy, Scotland, PH15 2BJ T: +44(0) 1 887 820 816 | F: +44(0) 1 887 820 844  
 E: [info@blueskytelemetry.com](mailto:info@blueskytelemetry.com) | W: [www.blueskytelemetry.com](http://www.blueskytelemetry.com)

© and made by WMI 2008



## TRX-1000S RECEIVER

Circuit Design:	Modern dual conversion superheterodyne circuit with 8 pole crystal filter and 40 dB AGC range
Manual Gain Range:	90 dB or better
Frequency Readout:	Digital, direct reading in 1 KHz steps; analog delta tune +/- 2 KHz from center frequency
Tuning:	Three-digit, dust resistant, push wheel switches control digital quartz-locked PLL synthesizer
Frequency Resetability:	To +/- 500 Hz
Signal Metering:	0-1 scale meter with high dynamic range circuit and backlight for night tracking. LED indicator gives linear signal strength-to-brightness response for night use Noise
Blanking Circuit:	Removes most impulse and ignition noise to enhance tracking in difficult conditions
Operating Voltage:	10-15 VDC through external DC jack (fused cigarette lighter cord included) or internal 10-AA cell nicad rechargeable battery pack.

### BlueSky Telemetry

The Corner, Crieff Road, Aberfeldy, Scotland, PH15 2BJ T: +44(0) 1 887 820 816 | F: +44(0) 1 887 820 844  
E: [info@blueskytelemetry.com](mailto:info@blueskytelemetry.com) | W: [www.blueskytelemetry.com](http://www.blueskytelemetry.com)

© and made by WMI 2008